

# Enabling WAN Web Server on SPA2100

Document ID: 108797

## Contents

[Introduction](#) [How do I enable WAN Web Server on SPA2100?](#) [Related Information](#)

## Introduction

This article is one in a series to assist in the setup, troubleshooting, and maintenance of Cisco Small Business products (formerly Linksys Business Series).

### Q. How do I enable WAN Web Server on SPA2100?

A.

There are two ways to enable WAN Web Server on SPA2100. This may be done through SPA2100's web-based interface or through the Interactive Voice Response (IVR) menu.

#### *Enabling WAN Web Server Through SPA2100's Web-Based Interface*

##### *Step 1:*

Access SPA2100's web-based interface. For instructions, click [here](#).

##### *Step 2:*

When the SPA2100's web-based interface appears, click **Admin Login** then **advanced** on the upper right-hand page.



The screenshot displays the SIPURA SPA2100 web-based interface. At the top left is the SIPURA logo with 'technology, inc.' below it. To the right, it says 'Sipura Phone A'. In the top right corner, there is a yellow box with the text 'Click Admin Log' and a yellow arrow pointing to a link labeled 'Admin Login'. Below the logo, there are two tabs: 'Router' (selected) and 'Voice'. Under the 'Router' tab, there are two sub-tabs: 'Status' (selected) and 'Wan Setup'. The main content area shows a table of system information:

Product Information			
Product Name:	SPA-2100	Serial Number:	000000000000
Software Version:	2.0.5(c)	Hardware Version:	1.0.0(99e2)
MAC Address:	000000000000	Client Certificate:	Installed
System Status			
Current Time:	1/1/2003 12:58:03	Elapsed Time:	00:58:03
Wan Connection Type:	DHCP	Current IP:	192.168.1.11
Host Name:	SipuraSPA	Domain:	
Current Netmask:	255.255.255.0	Current Gateway:	192.168.1.1
Primary DNS:	192.168.1.1		

**Note:** Access to the SPA2100's Admin Login-Advanced page does not require a password. SPA2100 units acquired through VoIP providers, however, are generally use password for

security reasons. This will deny access to the Admin Login and reject changes applied to existing voice configuration. If the unit is purchased from a reseller, it can be restored to default settings through factory reset using the IVR. For IVR instructions, click?here.

**Step 3:?**

Go to **WAN Setup**, look for **Remote Management** and set **Enable WAN Web Server** to **Yes**.

The screenshot shows the 'Sipura Phone Adapter Configuration' interface. The 'WAN Setup' tab is selected, indicated by a yellow callout box with the text 'Click WAN Setup.' The 'Remote Management' section contains the 'Enable WAN Web Server' dropdown menu, which is currently set to 'no'. A second yellow callout box points to this dropdown with the text 'Select Yes.' Other settings visible include 'Connection Type' (DHCP), 'Static IP Settings', 'PPPoE Settings', 'Optional Settings', and 'MAC Clone Settings'.

**Step 4:**

Click?  .

**Enabling WAN Web Server through SPA2100's Interactive Voice Response (IVR)**

**Step 1:?**

Dial **\*\*\*\*201#** on an analog phone connected to SPA2100.

**Step 2:**

Enter "1" to enable or "0" to disable the feature.

## Related Information

- **Technical Support & Documentation – Cisco Systems**
-

